

# Weather Satellite Receiver **APT-06 / APT-06 AD** Operating Manual



WRAASE electronic  
WeSaCom®-Systems  
Kronsberg 10  
24161 Altenholz  
Tel. 0431 32528  
Fax 0431 32579  
[www.wesacom.de](http://www.wesacom.de)  
E-mail: [info@wesacom.de](mailto:info@wesacom.de)

## **Weather Satellite Receivers APT-06 / APT-06AD** **Introduction and Leading Particulars**

The **APT-06** was especially designed to receive Polar Orbiter Weather Satellites in the 137 MHz VHF frequency range. It feeds the received, demodulated and filtered satellite image data into the sound input of a PC or laptop computer for further processing. In conjunction with special decoding and image display software an automatically operating weather satellite image reception station can be set up. At present time we believe, that „WX-to-Image“ is the ultimate software for this. Even the freeware version 2.7.3 can control the **APT-06** for fully unattended and automatic operation.

Besides automatic operation, the **APT-06** also offers manual control capability, which is helpful especially

during setup and for experiments. Furthermore the **APT-06** package comprises the Windows software program „**APT-CONTROL**“, which can be operated in a separate window besides the image decoding program. It allows detailed frequency- and other remote control functions on the **APT-06**.

An exactly matched receiver IF bandwidth of +/- 16 kHz together with an extremely linear demodulator guarantees the superior image quality and precise temperature calibration WRAASE / WeSaCom Systems are well known for.

Satellite frequency Doppler shift is precisely compensated by a special AFC-circuit, which is fully active already when the satellite comes up over the horizon. This eliminates noisy reception periods when the satellite is quickly approaching from long distance. In addition, an active filter circuit carefully matched to the satellite subcarrier frequency is implemented to reduce remaining noise components.

In the input rf amplifier high-quality Hi-Q-filters with silver plated and shielded helical coils provide a very high immunity against interference from strong signals in the close-by aviation and ham radio bands.

Due to the low noise figure (typical 1dB) of the built-in rf-amplifier an additional antenna amplifier normally is not necessary. However, when a long antenna feed must be used, an antenna preamplifier or an active antenna is advantageous because it compensates for the cable loss and thus increases the reception range. When using a WRAASE active antenna additional interference immunity is achieved due to additional Hi-Q-filtering. DC supply for the active antenna or the preamplifier is provided through the **APT-06** antenna socket(s) by simple insertion of a jumper plug on the rear panel.

At any time signal quality can be monitored by the built-in switchable speaker.

Undisturbed by any other signals, the built-in frequency scanner reliably locks only to weather satellites. It looks for the special weather satellite subcarrier frequency and will not hang on other signals like simple scanners do. Once a satellite has been found, the **APT-06** locks on its frequency as long as it is in the range of reception even if there are signal drop outs. The lock-in routine can be manually released at any time, which might be necessary if at the same time several satellites are in the range of reception and the scanner has locked on an unwanted one. Such ambiguity can only be avoided when having the **APT-06** frequency being controlled by the PC software via the serial interface. The “WX-to-Image” software (even in the freeware version) provides such capability and it controls the **APT-06** so that the proper channel is automatically selected for the next satellite to be recorded.


In addition, the advanced model **APT-06AD** contains an **Antenna Diversity Circuit**, which under difficult reception conditions provides means to effectively reduce signal drop-outs and noisy image sections. Such signal losses are in most cases caused by reflections, which result in several waves arriving at the antenna in different phase angles. Antenna-diversity uses the fact that when two antennas are used at slightly different locations, both antennas receive the waves in different phase conditions and it is therefore very unlikely that a minimum occurs at both antennas in the same moment. Continuously monitoring the signal and quickly switching between two antennas can eliminate drop outs and achieves nearly continuous reception quality.

The **APT-06AD** uses the noise value as switching criterion: A fast microprocessor continuously analyzes the signal-to-noise ratio and selects the less noisy antenna. Such antenna diversity based on noise evaluation is much more efficient than simple signal strength based circuits used by low-cost receivers, which in most cases switch antennas too early, too late or never.

The model **APT-06AD** applies advanced technology in the demodulator implementation: Besides the quadrature demodulator an especially designed phased locked loop circuit is used to precisely extract the image carrier creating additional 5 to 10 dB of noise margin. Thus the overall dynamic range of the receiver reaches exceptional 55 to 60 dB, compared to simple receivers which reach only 35 to 40 dB. Considering its outstanding receiving capabilities, the **APT-06AD** offers a very high price/performance value.

## Making the Connections & Operating the APT-06 / APT-06AD

The unit should only be AC-operated with the original power supply. Battery supply is possible from any 12V= source @ 100 mA. The **APT-06** has built-in voltage regulators, therefore no special considerations are necessary regarding voltage stability. Connection of DC in the wrong polarity will activate the built-in security circuit which disconnects power by a thermal fuse. Immediately remove the wrong polarization! After a short waiting time and as soon as the fuse has cooled down, the **APT-06** should work normally.



The **APT-06** has no power on-off switch. As soon as power is plugged in it powers up and the 5 red LEDs start blinking all together for about 5 seconds.

**Only applicable for the model APT-06AD:** You can activate the antenna diversity circuit by pressing the pushbutton (=>) once during the 5 seconds blinking period just after power-up. If you don't press the button during the blinking period, antenna diversity is not active and you can only activate it by a reset (unplug power and plug it in again) or by means of the program "**APT-CONTROL**". Operation of the antenna diversity circuit is indicated by the green LED, which informs the user which antenna is currently switched on. When no signal is received, it will be blinking (switching between antennas continuously).

**If antenna diversity is not activated only antenna input A is active.**

### Antenna Connection

It is strongly recommended to use a special weather satellite antenna with right-hand circular polarization (KX-137 or MX-137). Only with such antennas an interruption-free satellite pass and a coverage range of 4000 or more kilometers can be expected. If the antenna cable length is in the range of 20 to 30 m, an antenna preamplifier may not be necessary. Our preamplifier AA-137 or the active antennas KX-137 or MX-137, however, will in most cases improve reception-quality and -range as well as immunity against strong terrestrial signals because of the integrated high-Q-filters and the extremely low-noise transistors.

With our preamplifier AA-137 or an active antenna the standard RG-58U coaxial cable can be used without problems: Higher cable attenuation and / or slightly improper matching are fully compensated by the preamplifier.

In order to dc-supply a preamplifier or an active antenna without the need of an additional cable, DC-voltage of 10 V is provided on the antenna input socket (if the jumper is inserted at the rear panel). This is not needed when using the passive antenna model KX-137P but does on the other hand not represent a problem. There exist, however, other antenna constructions which represent a DC-short-circuit which would cause an immediate fuse-blow inside the APT-06 receiver. To avoid such a problem with passive antennas, it is strongly recommended to disconnect the DC antenna supply by simply removing the „ANT-DC“ marked jumper on the rear panel.

Whenever a passive antenna and no preamp is used, the jumper should be removed.

### Antenna Considerations

As the satellites circulate in a polar orbit, the antenna should have a free line-of-sight at least to north and south. Mounting the antenna under the roof is not recommended (although in some cases acceptable results are achieved). The height above ground is only critical with respect to the lowest possible line-of-sight elevation angle to the horizon and possible reduction of the shadowing effect of surrounding buildings. As a rule of thumb a line of sight to the horizon at an elevation angle of 10 to 15 degrees is sufficient. This only applies for buildings, trees are not so critical.

For good reception performance it is extremely important that the antenna is mounted in a **safe distance** to any possible radiation sources of broadband radio noise. Such sources of interference are **computers** and all devices which contain **microprocessors** or switching power supplies. The broad noise floor created by such devices (nowadays most electrical household equipment is suspicious) can easily cover the weak satellite signal. Noise reduction regulations keep such noise low but do not eliminate it in a close distance. Keeping the antenna in a distance of several meters from such devices will normally avoid such interference problems.

## Connection to the PC

Received satellite data are output through the „SOUND“ marked rear panel socket. Use the supplied standard cable to connect this socket with the sound input of your computer, preferably the „LINE-IN“ socket. In order to avoid power line hum interference (gray lines in the pictures) the PC and the receiver should be connected to the same power line outlet.

## OPERATION

### Software Set-up

The **APT-06** receiver works with any soundcard-based weather satellite reception software so that the user can choose among different programs available on the market. We recommend the program „**WX-to-Image**“ which delivers perfect results even in the freeware version and allows to add professional features at very moderate cost when being upgraded via the internet. The freeware version already offers all major functions and supports automatic computer controlled frequency selection of the **APT-06**. (Since version 2.8.14c).

Read the software instructions which contain all the necessary information for proper installation and software setup. Most important for good results is the first-time setting of the correct audio level. There are two controls with basically the same effect: First the Windows Mixer Control and second the **APT-06** hardware control which can be reached through the hole in the front panel (use small screwdriver). In the „WX-to-Image“ program window there is a level meter in the right bottom corner which should show green color (50 to 80 %) when receiving a signal (FILE / RECORD / MANUAL TEST). You must find the correct level either by modifying the setting of the Windows Mixer, the APT-06 level control or both.

### Receiving Operations

After power-up the receiver will start in the scanning mode. The 5 fixed frequency channels are assigned as follows (from left to right):

- (1) 137.100 MHz NOAA18
- (2) 137.400 MHz -.-
- (3) 137.500 MHz NOAA15
- (4) 137.620 MHz NOAA17
- (5) 137.9125 MHz NOAA18 (alternate frequency)

At present time all available satellites are covered by these frequency channels. Further channels may be added with a future firmware update. As soon as a satellite appears on one of the channels, scanning will

stop and resume a few seconds after the satellite signal has permanently disappeared. To stop scanning and to activate manual mode, press the pushbutton (=>) once. Every further hit of the button will advance the channel. To reactivate scanning, press and hold the button and as soon as all 5 LEDs light, release it.

The **APT-06** weather satellite receiver operates completely automatically, no user intervention is needed: In the "Auto Record" mode of the "WX-to-Image" program the images will be recorded and processed according to the settings in the software. Images may be automatically uploaded to a website.

You can at any time check the signal quality by pressing the „SP-ON“ pushbutton which activates the built-in loudspeaker.

## **APT-06 Computer Control via RS232**

In scanning mode it may happen that in certain overlapping orbit constellations two satellites are in the range of reception and the **APT-06** locks to the unwanted one. Such ambiguity can only be avoided when having the **APT-06** frequency being controlled by the PC software via the serial interface. The "WX-to-Image" software (even in the freeware version) provides such capability and it controls the **APT-06** so that the proper channel is automatically selected for the next satellite to be recorded.

Connect the **APT-06** with the supplied serial cable to a free COMPORT of your computer. If the computer does not have a COMPORT, an adapter cable USB RS232 may be used. In "WX-to-Image" open the "Options / Recording Options" menu. In the "receiver type" box select "**APT-06**" and leave the baudrate setting with "receiver default". In the "receiver port" box select the COMPORT you have connected the **APT-06** to. When using an USB adapter, you should have already installed the associated software, which has created a virtual COMPORT. If you are not sure about the number, check in the Windows System Control.


„WX-to-Image“ has a built-in satellite tracking module and automatically selects the correct channel for the next satellite to be received and sets the **APT-06** to scanning mode after the image has been recorded.

## **PC Control Software „APT-CONTROL“**

The supplied software program **APT-CONTROL** offers additional comfortable control functions and works under all Windows versions from Windows95 on. It can be operated in a separate window parallel to the recording software. Keep in mind, that the serial port can only be controlled by one program at a time and that therefore "WX-to-Image" will not control the receiver as long as **APT-CONTROL** is active.

**APT-CONTROL** does not require a special installation procedure. Just copy the file APT\_CONTROL.EXE to your computer and create a connection to the Desktop.

Operation is most self explanatory. After selection of the proper COMPORT try out the settings in the „Priority CHANNEL“ section and check if the proper LEDs on the **APT-06** light.



**APT-CONTROL** offers several frequency selection options: While in the field „Priority-Channel“ the fixed channels within the **APT-06** firmware are selected, the other frequency control options directly access the **APT-06** digital synthesizer which allows arbitrary frequency selection in the range from 134 to 141 MHz (note that full receiver performance is only guaranteed between 137 and 138 MHz).

First there are edit-boxes for direct numerical frequency input from the keyboard, which require entry in Hertz ( 9 digits) and second there is a mouse or arrow-key operated “Frequency Tuning” tool. Select the step-size of the slider in the field “Set Tuning Stepsize”. To set the receiver **APT-06** to the frequency being selected and displayed in the large display field click the button “Send Frequency”. To indicate reception of such external frequency commands the left 3 LEDs on the **APT-06** will light.

In the right-hand field of the program window there is a vertical row of 10 frequency input boxes. These can be used to enter up to 10 preferred frequencies. These values will be permanently stored on the computer so that you don’t lose them when you exit **APT-CONTROL**. Clicking the radio button left of the edit box will set the receiver to that frequency.

On the right-hand side of the frequency edit boxes there are check boxes, which allow to create a selection of frequencies for scanning.

Scanning will be activated by clicking the button „Scan Selection“ and deactivated by clicking it again. In the edit box “Speed (ms)” you can set the scanning speed from 1 second to 10 seconds (must be entered in milliseconds). Any change of speed requires a new start of scanning to come into effect. Upon reception of a satellite the frequency will be locked and kept stable for undisturbed image recording. **APT-CONTROL** continues sending the frequency commands to the receiver; however these commands are neglected as long as the **APT-06** has locked to a satellite being in the range of reception.

The operations in the field “Antenna Diversity” apply to the model **APT-06AD** only.

Here, the antenna diversity functions can be controlled independently from previous selections made on the hardware.

“Diversity ON” activates the antenna diversity circuit.

“Antenna A” deactivates antenna diversity and selects antenna A.

“Antenna B” deactivates antenna diversity and selects antenna B.

The green LED on the **APT-06AD** front panel indicates which antenna is active: Green LED off = Antenna A is on; green LED on = Antenna B is on.

## Safety Instructions

The **APT-06** complies with the European Standards for Electromagnetic Immunity and carries the CE sign. The weather satellites which the **APT-06** is designed to receive, transmit unencrypted data and can be received worldwide in equal quality. In Germany reception is generally permitted and free of charge. In other countries other regulation may apply.

1. This appliance may only be used for the designated purpose. It may only be used with grounded or isolated power supplies according to VDE regulations.
2. This appliance is designated for use in rooms and a dry and dust free environment at room temperature between +5° and +35° C.
3. It must be made sure that all wires and cables are carefully installed so that nobody can stumble nor can be caught by them. Do never tear or twist the cables.
4. Electrical appliances which are connected to the **APT-06** like computers must be properly grounded to avoid electrical shocks. Disconnect the unit from power if it is not used for a longer period.
5. Keep any plastic bags used for packing from children and animals.

## Technical Data, common for APT-06 and APT-06AD

Frequency range: 137-138 MHz (134-141 MHz at reduced performance)

Channel step size: 10kHz

Fixed hardware-channels: 5 (by firmware extendable to 9)

Arbitrary channels, set by software: 10

Sensitivity: 0,26µV @ 20dB S/N

AF-Output level: 0 to 1000mVpp (1kΩ)

AFC-pulling range ±10kHz

Power supply: 12V, max. 100mA

Size: 105x105x30mm / 2mm thick aluminum case.

Operating controls: Channel /mode selection pushbutton,  
Speaker-ON pushbutton.

5 LEDs for channel & mode indication,

1 LED for antenna diversity indication (APT-06AD only)

Antenna inputs(s): 50Ω ,BNC (APT-06AD has 2 of each)

Serial port: 9-pin D-SUB (female), 1200Bd.

## Differences APT-06 / APT-06AD

	APT-06	APT-06AD
Image demodulator	Quadraturdemodulator	PLL-Demodulator
Total dynamic range	> 45 dB	> 55 dB
Antenna-Diversity:	no	yes

Please support us by placing links to our website:

[www.wesacom.de](http://www.wesacom.de) or [www.wraase.de](http://www.wraase.de)

